

The Bowers BEST T2 Amorphous Transformer is the lowest loss Amorphous Transformer currently on the UK market.

KVA	Pre 2015 EU Directive Standard Losses		EU Directive Tier 1 losses Bowers standard Range CRGO		Bowers BEST T1 Amorphous Range		EU Directive Tier 2 losses 2021		Bowers BEST T2 Amorphous Range	
	NLL	LL	NLL	LL	NLL	LL	NLL	LL	NLL	LL
	Watts	Watts	Watts	Watts	Watts	Watts	Watts	Watts	Watts	Watts
315	650	6000	360	3900	165	3880	324	2800	160	2645
500	900	7200	510	5500	230	5480	459	3900	230	3765
800	1350	10000	650	8400	280	8340	585	6000	315	5705
1000	1550	12500	770	10500	340	10235	693	7600	375	7205
1250	1800	14000	950	11000	385	10950	855	9500	430	9025
1500	2100	19000	1130	13140	445	13035	1015	11286	485	10760
1600	2100	21600	1200	14000	485	13920	1080	12000	535	11400
2000	2300	25000	1450	18000	525	17690	1305	15000	605	14320
2500	3300	28000	1750	22000	690	21850	1575	18500	745	17690
3150	3300	40000	2200	27500	885	27440	1980	23000	985	21850